


Revised 12/19/23



### **CONTROLS AND FEATURES**

- Level
- Tone
- Distortion

All trademarks and registered trademarks are the property of their respective owners. The company, product, and service names used in this web site are for identification purposes only. Use of these names, logos, and brands does not imply endorsement.




Parts List (Page 1 of 1)

| LOCATION       | VALUE   | TYPE                              | NOTES                           |
|----------------|---------|-----------------------------------|---------------------------------|
| R1             | 10K     | Resistor, 1/4W                    |                                 |
| R2             | 100K    | Resistor, 1/4W                    |                                 |
| R3             | 470K    | Resistor, 1/4W                    |                                 |
| R4             | 10K     | Resistor, 1/4W                    |                                 |
| R5             | 100R    | Resistor, 1/4W                    |                                 |
| R6             | 1K      | Resistor, 1/4W                    |                                 |
| R7             | 10K     | Resistor, 1/4W                    |                                 |
| R8             | 100K    | Resistor, 1/4W                    |                                 |
| R9             | 470K    | Resistor, 1/4W                    |                                 |
| R10            | 10K     | Resistor, 1/4W                    |                                 |
| R11            | 180R    | Resistor, 1/4W                    |                                 |
| R12            | 10K     | Resistor, 1/4W                    |                                 |
| R13            | 100K    | Resistor, 1/4W                    |                                 |
| R14            | 470K    |                                   |                                 |
| N 14           |         | Resistor, 1/4W                    |                                 |
| R15            | 10K     | Resistor, 1/4W                    |                                 |
| R16            | 180R    | Resistor, 1/4W                    |                                 |
| R17            | 47K     | Resistor, 1/4W                    |                                 |
| R18            | 22K     | Resistor, 1/4W                    |                                 |
| R19            | 33K     | Resistor, 1/4W                    |                                 |
| R20            | 220K    | Resistor, 1/4W                    |                                 |
| R21            | 5K6     | Resistor, 1/4W                    |                                 |
| R22            | 1K      | Resistor, 1/4W                    |                                 |
| R23            | 1M      | Resistor, 1/4W                    |                                 |
| R24            | 10K     | Resistor, 1/4W                    |                                 |
| R25            | 47K     | Resistor, 1/4W                    |                                 |
| R26            | 47K     | Resistor, 1/4W                    |                                 |
| R27            | 10K     | Resistor, 1/4W                    |                                 |
| R28            | 10K     | Resistor, 1/4W                    |                                 |
| CLR            | 4K7     | Resistor, 1/4W                    | * LED current limiting resistor |
| <u></u>        |         |                                   |                                 |
| C1             | 1u      | Electrolytic capacitor, 5mm       |                                 |
| C2             | 330p    | Ceramic capacitor                 |                                 |
| C3             | 1u      | Electrolytic capacitor, 5mm       |                                 |
| C3<br>C4<br>C5 | 1u      | Electrolytic capacitor, 5mm       |                                 |
| C5             | 100n    | Film capacitor, 7.2 x 2.5mm       |                                 |
| C6             | 330p    | Ceramic capacitor                 |                                 |
| C6<br>C7       | 1u      | Electrolytic capacitor, 5mm       |                                 |
| C8             | 100n    | Film capacitor, 7.2 x 2.5mm       |                                 |
| C9             | 330p    |                                   |                                 |
| C10            |         | Ceramic capacitor                 |                                 |
|                | 1u      | Electrolytic capacitor, 5mm       |                                 |
| C11            | 10u     | Electrolytic capacitor, 5mm       |                                 |
| C12            | 1u      | Electrolytic capacitor, 5mm       |                                 |
| C13            | 1u      | Electrolytic capacitor, 5mm       |                                 |
| C15            | 2n2     | Film capacitor, 7.2 x 2.5mm       |                                 |
| C16            | 47n     | Film capacitor, 7.2 x 2.5mm       |                                 |
| C17            | 47n     | Film capacitor, 7.2 x 2.5mm       |                                 |
| C100           | 100u    | Electrolytic capacitor, 5mm       |                                 |
|                |         |                                   |                                 |
| D1             | 1N914   | Signal diode, DO-35               |                                 |
| D2             | 1N914   | Signal diode, DO-35               |                                 |
| D3             | 1N914   | Signal diode, DO-35               |                                 |
| D4             | 1N914   | Signal diode, DO-35               |                                 |
| D100           | 1N5817  | Schottky diode, DO-41             |                                 |
|                |         |                                   |                                 |
| Q1             | 2N5088  | BJT transistor, NPN TO-92         |                                 |
| Q2             | 2N5088  | BJT transistor, NPN TO-92         |                                 |
| Q3             | 2N5088  | BJT transistor, NPN TO-92         |                                 |
| Q4             | 2N5088  | BJT transistor, NPN TO-92         |                                 |
|                | 2.10000 | 501 (1011010101, 141 14 10 02     |                                 |
| LEVEL          | B100K   | 16mm right-angle PCB mount pot    |                                 |
| TONE           | B100K   | 16mm right-angle PCB mount pot    |                                 |
| DIST           | B100K   | 16mm right-angle PCB mount pot    |                                 |
| וטוטו          | אטטו ט  | Tromini ngmi-angie F CD mount pot |                                 |




Schematic Diagram





Wiring Diagram





Drill Template

125B Enclosure

