




Thunder Pipe Overdrive


Revised 4/7/21



CONTROLS AND FEATURES

- Preamp
- Midrange
- Focus
- Gain
- Tone
- Level

All trademarks and registered trademarks are the property of their respective owners. The company, product, and service names used in this web site are for identification purposes only. Use of these names, logos, and brands does not imply endorsement.



LOCATION	VALUE	TYPE	NOTES
R1	2M2	Resistor, 1/4W	
R2	470K	Resistor, 1/4W	
R3	47K	Resistor, 1/4W	
R4	10K	Resistor, 1/4W	
R5	390R	Resistor, 1/4W	
R6	10K	Resistor, 1/4W	
R7	100K	Resistor, 1/4W	
R8	470K	Resistor, 1/4W	
R9	12K	Resistor, 1/4W	
R10	100R	Resistor, 1/4W	
R11	1K	Resistor, 1/4W	
R12	12K	Resistor, 1/4W	
R13	470K	Resistor, 1/4W	
R14	100K	Resistor, 1/4W	
R15	12K	Resistor, 1/4W	
R16	390R	Resistor, 1/4W	
R17	10K	Resistor, 1/4W	
R18	470K	Resistor, 1/4W	
R19	100K	Resistor, 1/4W	
R20	12K	Resistor, 1/4W	
R21	100R	Resistor, 1/4W	
R22	3K3	Resistor, 1/4W	
R23	56K	Resistor, 1/4W	
R24	470K	Resistor, 1/4W	
R25	100K	Resistor, 1/4W	
R26	10K	Resistor, 1/4W	
R27	1K8	Resistor, 1/4W	
R100	4K7	Resistor, 1/4W	
C1	100n	Film capacitor, 7.2 x 2.5mm	
C2	100n	Film capacitor, 7.2 x 2.5mm	
C3	100n	Film capacitor, 7.2 x 2.5mm	
C4	6n8	Film capacitor, 7.2 x 2.5mm	
C5	1u	Film capacitor, 7.2 x 5.0mm	
C6	470p	Ceramic capacitor	
C7	100n	Film capacitor, 7.2 x 2.5mm	
C8	100n	Film capacitor, 7.2 x 2.5mm	
C9	470p	Ceramic capacitor	
C10	100n	Film capacitor, 7.2 x 2.5mm	
C11	100n	Film capacitor, 7.2 x 2.5mm	
C12	470p	Ceramic capacitor	
C13	100n	Film capacitor, 7.2 x 2.5mm	
C14	3n3	Film capacitor, 7.2 x 2.5mm	
C15	47n	Film capacitor, 7.2 x 2.5mm	
C16	47n	Film capacitor, 7.2 x 2.5mm	
C17	100n	Film capacitor, 7.2 x 2.5mm	
C18	100n	Film capacitor, 7.2 x 2.5mm	
C100	100u	Electrolytic capacitor, 5mm	

